DIGITUS PoE+ Injector, 802.3at, 30 Watt

DN-95103-2 4016032375951



DIGITUS PoE+ Injector, 802.3at 10/100/1000 Mbps Output max. 48V, 30W

Reduce cabling for Wireless APs, IP Phone and any PoE-ready device

The Digitus PoE Injector allows you to minimize cabling during installation of PoE-ready devices such as IP network cameras. Data supply and power supply to the devices is accomplished using a single Ethernet cable. This makes laying a separate power cable unnecessary and allows you to extend your network to places where there are no outlets or power cables. The Injector is completely compliant with the IEEE802.3at standard and delivers an output power of 30 watts.

- Complies with the 802.3at PoE+ and the 802.3af PoE standard
- 1 Easily merge of power and data cables into a single cable
- Extend your network to places where there are no power supply cables or sockets available
- 1 no setup needed
- Supports all IEEE 802.3at-compliant PoE devices (such as access points, VoIP telephones, and IP cameras)
- Transmission range of up to 100 m with an additional PoE extender, this can be increased to up to 400 m
- Internal consumption (full loaded): 7.0 W max.
- Input: 1x RJ-45 (data)
- Output: 1x RJ-45 (power and data)
- Data output: 100/100/1000 Mbps Gigabit
- Power output: 30 W
- Output voltage: 48 V DC
- Operating temperature range: -5 °C to +40 °C
- Dimensions: 140 mm x 63 mm x 32.5 mm
- Weight: 200g
- The output is equipped with a current limit, a short-circuit fuse and automatic terminal device recognition and

Package Content

- 1 PoE Injector
- QIG (quick installation guide)
- 1 Power Supply





www.assmann.com

DIGITUS PoE+ Injector, 802.3at, 30 Watt

DN-95103-2 4016032375951



→ Logistics	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	40	16,20	53,00	35,00	31,00	57505,00
Packaging Unit Inside	1	0,41	16,50	13,80	5,00	1138,50
Packaging Unit Single	1	0,41	16,50	13,80	5,00	1138,50
Net single without Packaging	1	0,00	14,00	6,20	3,20	277,76

→ Packaging type









www.assmann.com 2/2