

ASUS PRIME B650M-A WIFI II AMD B650 Socket AM5 micro ATX

Merk : ASUS

Artikelcode: 90MB1EG0-M0EAY0

Productnaam : PRIME B650M-A WIFI II

ASUS PRIME B650M-A WIFI II. Processorfabrikant: AMD, Processor socket: Socket AM5, Compatibele processors: AMD Ryzen™ 7. Ondersteunde geheugen types: DDR5-SDRAM, Maximum intern geheugen: 128 GB, Geheugen slots type: DIMM. Ondersteunde opslagstationinterfaces: M.2, PCI Express 4.0, PCI Express 5.0, SATA, Ondersteunde types opslag-drives: HDD & SSD, Soorten RAID: 0, 1, 10. USB-connectortype: USB Type-A. Ethernet interface type: 2.5 Gigabit Ethernet, Wifi-standaard: Wi-Fi 6 (802.11ax), Wi-Fi-standaarden: 802.11a, 802.11b, 802.11g, Wi-Fi 4 (802.11n), Wi-Fi 5 (802.11ac), Wi-Fi 6 (802.11ax)



Processor		Aansluitingen achterzijde	
Processorfabrikant *	AMD	Aantal USB 2.0-poorten *	4
Processor socket *	Socket AM5	Aantal poorten USB 3.2 Gen 1 (3.1 Gen 1) Type A *	2
Compatibele processors *	AMD Ryzen™ 7	Aantal poorten USB 3.2 Gen 2 (3.1 Gen 2) Type A *	2
Geheugen		Aantal Ethernet LAN (RJ-45)-poorten *	1
Ondersteunde geheugen types *	DDR5-SDRAM	VGA (D-Sub)poort(en) *	1
Aantal geheugenslots *	4	Aantal HDMI-poorten *	1
Geheugen slots type	DIMM	Aantal DisplayPorts	1
Geheugen kanaal	Dubbelkanaals	Hoofdtelefoonuitgangen	1
ECC-compatibiliteit	ECC & Niet-ECC	Lijningang	✓
Supported memory clock speeds	4800,5000,5200,5400,5600,5800,6000,6200,6400 MHz	Microfoon, line-in ingang	✓
Maximum intern geheugen *	128 GB	USB-connectortype	USB Type-A
Niet gebufferd geheugen	✓	Netwerk	
Opslag-controllers		Ethernet LAN	✓
Ondersteunde types opslag-drives	HDD & SSD	Ethernet interface type	2.5 Gigabit Ethernet
Ondersteunde opslagstationinterfaces *	M.2, PCI Express 4.0, PCI Express 5.0, SATA	Wifi *	✓
Maximum aantal HDD's per behuizing	4	Wifi-standaard	Wi-Fi 6 (802.11ax)
Aantal storage drives ondersteund	2	Wifi-standaarden	802.11a, 802.11b, 802.11g, Wi-Fi 4 (802.11n), Wi-Fi 5 (802.11ac), Wi-Fi 6 (802.11ax)
RAID support	✓	Bluetooth	✓
Soorten RAID	0, 1, 10	Bluetooth-versie	5.2
Interne aansluitingen		Kenmerken	
USB 2.0 aansluitingen *	2	Chipset moederbord *	AMD B650
USB 3.2 Gen 1 (3.1 Gen 1)-aansluitingen *	2	Audio-uitgangskanalen *	7.1 kanalen
Aantal SATA-aansluitingen	4	Component voor *	PC
Totaal aantal SATA-connectoren	4	Moederbord form factor *	micro ATX
S/PDIF uitgang	✓	Moederbord chipset familie *	AMD
Audioconnector	✓	Type stroombron	ATX
Voorpaneel-connector	✓	Ondersteunt Windows	Windows 10, Windows 11
ATX Power connector (24-pin)	✓		

Interne aansluitingen			Uitbreidingsmodules		
Aansluiting voor ventilator van voeding	✓		PCI Express x16 (Gen 4.x) sleuven	3	
Aansluiting voor CPU koeler	✓		BIOS		
Aansluitingen voor behuizingsventilatoren	3		BIOS type *	UEFI AMI	
Peripheral (Molex) power connectors (4-pin)	4		Grootte BIOS-geheugen	256 Mbit	
EPS power connector (8-pin)	✓		Clear CMOS knop	✓	
COM aansluitingen	1		Gewicht en omvang		
TPM connector	✓		Breedte	244 mm	
12V vermogen-connector	✓		Diepte	244 mm	
RGB LED-aansluitrail	✓		Inhoud van de verpakking		
			Meegeleverde kabels	SATA	
				ASUS Exclusive Software Armoury Crate - Aura Creator - Aura Sync - Fan Xpert 2+ - Power Saving AI Suite 3 - TurboV EVO - DIGI+ VRM - PC Cleaner ASUS CPU-Z MyASUS Norton Anti-virus software (Free Trial version) WinRAR UEFI BIOS ASUS EZ DIY - ASUS CrashFree BIOS 3 - ASUS EZ Flash 3 - ASUS UEFI BIOS EZ Mode	
			Meegeleverde software		



4711387034934

Catalog Object Cloud



Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.